



## SYSTEM OPTIONS

System	AREA	<b>A/P</b>	H/A
Closing Code	<b>NO</b>	YES	
Closing Check	<b>NO</b>	YES	
Entry Delay 1	--	(30 to 250 sec., default = 30)	
Entry Delay 2	--	(30 to 250 sec., default = 60)	
Exit Delay	--	(45 to 250 sec., default = 60)	
Cross Zone Time	--	<b>(0, 4 to 250 sec.)</b>	
Power Fail Delay	--	(0, <b>1</b> to 9 hrs.)	
Reset Swinger Bypass	<b>NO</b>	YES	
Telephone Access	<b>NO</b>	YES	
Zone Activity Hours	--	<b>(0 to 9 hrs.)</b>	
Arm Activity Days	--	<b>(0 to 99 days)</b>	
Time Change	NO	<b>YES</b>	
Hours from GMT	--	(0 to 23 hrs., default = 6)	
Time Display	NO	<b>YES</b>	
House Code	--	<b>(0 to 50)</b>	
Detect Wireless Jamming	<b>NO</b>	YES	
Wireless Audibles	ANY	<b>DAY</b> MIN	
Enable Keypad Panic Keys	NO	<b>YES</b>	
Occupied Premises	NO	<b>YES</b>	

## BELL OPTIONS

Bell Cutoff Time	--	(0 to 15 min., default = 5)
Automatic Bell Test	<b>NO</b>	YES
Bell Output	--	<b>(0 to 4, 31-34, 41-44)</b>

### Bell Action . . .

Fire Zones	Steady	<b>Pulse</b>	Temporal	None
Burglary Zones	<b>Steady</b>	Pulse	Temporal	None
Supervisory Zones	Steady	Pulse	Temporal	<b>None</b>
Panic Zones	Steady	Pulse	Temporal	<b>None</b>
Emergency Zones	Steady	Pulse	Temporal	<b>None</b>
Auxiliary 1 Zones	Steady	Pulse	Temporal	<b>None</b>
Auxiliary 2 Zones	Steady	Pulse	Temporal	<b>None</b>

## OUTPUT OPTIONS

Cutoff Output	1	2	3	4
Cutoff Time	--	(0 to 15 min.)		
Comm Fail Output	--	(0 to 4, 31-34, 41-44)		
Fire Alarm Output	--	(0 to 4, 31-34, 41-44)		
Fire Trouble Output	--	(0 to 4, 31-34, 41-44)		
Ambush Output	--	(0 to 4, 31-34, 41-44)		
Entry Output	--	(0 to 4, 31-34, 41-44)		
Exit Output	--	(0 to 4, 31-34, 41-44)		
Ready Output	--	(0 to 4, 31-34, 41-44)		
Armed Output	--	(0 to 4, 31-34, 41-44)		
Burglary Output	--	(0 to 4, 31-34, 41-44)		
Late To Close Output	--	(0 to 4, 31-34, 41-44)		
Arm-Alarm Output	--	(0 to 4, 31-34, 41-44)		

## OUTPUT INFORMATION (WIRELESS)

Output No. *	Output Name	Serial Number	Superv. Time (0, 3, 60, 240 min.)
31			
32			
33			
34			
41			
42			
43			
44			

**Note:** Assign Output Numbers 31 to 34 for slow response time wireless outputs (activates within 15 seconds) or 41 to 44 for fast response time wireless outputs (activates within 1 second).

## AREA INFORMATION

Area #	Area Name	Auto Arming N or Y	Bad Zones BYP, FORC, or REF	Auto Disarm N or Y
1				
2				
3				
4				
5				
6				

**Note:** Factory default values are shown in bold type.



