

## Introduction

DMP XTL .....	1
DMP XT30 .....	3
DMP XT50 .....	5
DMP XR100/XR100N.....	7
DMP XR500/XR500N/XR500E .....	9

## Introduction

DMP products offer solutions to multiple access control, burglary, and fire security applications. The DMP family compares well with many existing products from competitor companies.

This document is designed to identify the features and capabilities of DMP products and compare them to the features and capabilities of competitor products.

DMP solutions are customer-driven. We strive to ensure our customers and potential customers have the best products to meet their needs without having to exceed their budgetary requirements. Additionally, DMP solutions offer future expansion with a minimum of cost whenever possible.

As new products and options are developed every effort is made to ensure those new products are backward compatible. Where backward compatibility is not feasible, DMP works closely with the customer to design solutions that provide the customer the best product for the specific application.

**IMPORTANT!** The comparison information included is from distributors, equipment manufacturers and their published specifications. DMP is not responsible for errors or changes.

## DMP PRODUCT COMPARISON GUIDE



**DMP XTL**

The DMP XTL Wireless Security System operates via cellular communications. It offers 30 user codes with authority levels, 28 wireless zones, and a 100-event memory. It supports up to six areas, four two-way wireless keypads and eight fobs.

**Compares to:**

DSC	Alexsor, Power Series 9047
GE Interlogix	Simon XT
Honeywell	Lynx Plus,
Visonic	Power Max Express, Power Max Pro
2GIG Technologies	Go Control

	DMP XTL	DSC-Alexsor	DSC-Power 9047	GE-Simon XT	Honeywell LYNX Plus	Visonic Power Max Express	2GIG Tech Go Control
<b>Zone Information</b>							
Maximum Wireless Zones	28	32	32	40	39	28	48
Control Panel Zones	0	No	2	2	1	1	2
Wireless Expansion Zones	28	32	32	38 if using 2 on-board zones	39	28	48
RF Operating Frequencies	903-927 MHz	433 MHz	433 MHz	319 MHz Bandwidth 350 kHz	345 MHz	315 MHz (in USA & Canada)	433 MHz
<b>Keypad/Access Information</b>							
Supervised Keypads	up to 4 DMP 9060/9063 Two-Way wireless Keypads	up to 4 WT5500 2-way Wire-free Keypads	No	No	5828 and 5828V wireless keypads	up to 8 non display wireless keypads (Remote Commanders) and 2 two-way keypads	4 Wireless2GIG-PAD1 Keypads
Built-in Keypad	No	No	Yes	Yes	Yes	Yes	Yes
Keypad back lighting turns red on alarm	Yes	No	No	No	No	No	No
Wireless Siren	Yes	No	No	No	Yes	No	Yes
Tamper	Yes	Yes	No	No	No	No	No
Enclosure / Panel Mounting	Wall Mount	Wall Mount	Wall Mount	Wall Mount and desktop version	Wall or optional desktop mounting	Wall Mount	Wall or optional desktop mounting
Standby Backup Power Rating	24 hours	24 hours	No	24 hours	24 hours	12 hours	24 hours
<b>User Information</b>							
User Codes/Access Cards	30 user codes with Master/Standard Authority Levels	16 user codes 1 master code and 1 maintenance code	16 user codes 1 master code	1 Master code and 8 standard codes	8	8 (4 digit user codes)	8
Event Memory	100	500	128	100	84 event log	No	No
Individual Zone Monitor	Yes	Yes	No	Yes	Yes	Yes	Yes
<b>MyAccess™ Features</b>							
-Control via Cell Text Messages	Yes	No	No	Yes	Yes (optional)	No	Yes
-Email/Text Messages of System Activity	Yes	No	No	Yes	Yes (optional)	No	Yes
<b>System Information</b>							
E-Mail	Yes	No	No	Yes with optional GSM Module and service	Requires Honeywell Total Connect Subscription	No	Yes
SMS TXT Messaging direct from the panel	Yes	No	No	No	No	No	No
Areas	6	No	No	No	No	4	No
Arming Modes	Area/All-Perim/ Home-Sleep-Away	Stay/Away	Stay/Away	Stay/Away	Stay/Away	AWAY, HOME, AWAY-INSTANT, HOME-INSTANT, LATCHKEY, FORCED, BYPASS	Stay/Away
Communication formats	SDLC via cellular	No	No	SIA or CID	Ademco Express/Contact ID/ Ademco Low Speed/Radionic/SESCOIA 20PPS	SIA, Contact ID, SIA/IP	No
Remote Downloadable over Cell	Yes	Yes Remote	Yes Remote	Yes	Yes	No	Yes
Remote Control	Yes	No	Yes	No	Yes	Yes	Yes

**DMP XTL (continued)**

	DMP XTL	DSC Alexsor	DSC Power 9047	GE-Simon XT	Honeywell LYNX Plus	Visonic Power Max Express	2GIG Tech Go Control
<b>Communication</b>							
Communications	Cell	Cell/Dialer	Dialer	Cell/Dialer	Cell/Dialer	Cell/Dialer	Cell
Cellular Support	GSM	GSM/IP	No	GSM	GSM	Optional Built in GSM/GPRS Communicator	GSM
<b>Audible Devices</b>							
Siren	Wireless Siren, 85db	On-Board Siren and or up to 4 indoor and outdoor 2-way wireless sirens.	Yes	On-Board	85 dB internal sounder with voice siren	Built in Piezo and up to two wireless sirens	Yes
<b>Wireless Information</b>							
Wireless Arm/Disarm	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Built in Wireless receiver	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Wireless Types Supported	DMP 1100 Series 900 MHz Spread Spectrum 2 way wireless.	All DSC433 MHz wireless devices	All DSC433 MHz wireless devices	Both GE Crystal and SAW wireless devices.	Honeywell 5800 Series Wireless Devices	Visonic Wireless Products	2GIG wirelss devices
<b>DMP Features</b>							
Attrition Detection (used to give advanced warning that customer may be preparing to cancel their monitoring contract)	Yes	No	No	Yes	Yes	No	No
User Check In (manage Latchkey children)	Yes	No	No	Yes	Via Pager Function or E-mail	Yes	No
Programmable Inactivity Monitor to watch for on-site activity	Yes	No	No	No Activity Report	No	Yes	No
<b>False Alarm Reduction Features</b>							
Exit Error	Yes	Yes	No	No	Yes	No	No
Fire Verify Zones	Yes	No	No	No	No	No	No
Cross Zoning	Yes	No	No	No	No	Yes	No
Abort Reporting	Yes	No	No	No	No	Yes	No
System Test by User	Yes	Yes	No	No	Yes	Yes	No
System Recently Armed	Yes	No	No	No		No	No
Programmable Entry/Exit Delays per SIA-CP01	Yes	Yes	Yes	No	LynxSIA Plus	Yes	No
Transmit Delay	Yes	No	No	No	No	No	No
Swinger Zone Bypassing	Yes	Yes	No	No	Yes	Yes	No
Report Bypass to Central Station	Yes	Yes	No	No	Yes	Yes	Yes
Unique Duress Code	Yes	Yes but takes up a standard code location	No	No	User #8	Yes	No
Cancel / Verify reporting	Yes	No	No	No	No	No	No
<b>Compliance</b>							
UL 1023 Household Burglar	Yes	Yes	Yes	Yes	No	Yes	Yes
UL 1610 Central Station Burg	Yes	No	No	No	No	No	No
UL 985 Household Fire Warn	Yes	Yes	Yes	Yes	No	Yes	Yes
ULC Listing ORD-C102319-74	No	Yes	Yes	Yes	No	Yes	Yes
UL1637	No	No	No	No	No	No	No
UL 1635	No	No	No	Yes	No	No	No
ULC-5545-M89	No	Yes	Yes	Yes	No	Yes	Yes
CSFM	Yes	No	Yes	Yes	No	No	No
SIA-CP01	Yes	Yes	Yes	Yes	Must use the LynxSIA Plus	Yes	Yes

**DMP XT30**

The DMP XT30 offers everything you want in one panel - built-in Network, Cellular, and Dialer communications. The XT30 can be expanded to 30 zones by adding hardwire zones or 1100 Series wireless zones to meet the protection requirements of any mid-range and high-end residential or commercial installation. The XT30 provides 10 on-board zones, one 2-wire smoke detector zone, 20 keypad bus zones, door access capability, ethernet, cellular, Pager Direct™ paging, 30 user codes, and daily opening/closing and relay output schedules.

**Compares to:**

Ademco Vista 105E, 15P  
 DSC Power 432, PC1616, PC1832, Power 632  
 GE Interlogix Concord Express  
 Bosch D2212, D2412, D4412  
 Napco GEM-P816, GEM-P1632

	DMP XT30	DSC Power 432	DSC PC1616	DSC PC1832	DSC Power 632	Ademco Vista-105E	Ademco Vista 15P	Napco GEM-P816	Napco GEM-P1632	GE Concord Express	Bosch D2212B	Bosch D4412
<b>Zone Information</b>												
Maximum Zones	42	32	16	32	32	22	32	16	32	24	24	24
Control Panel Zones	10	4	6	8	6	6	6	8	8	6	8	8
Control Panel Fire Zones	1	No	No	No	No	0	1	2	2	1	1	1
Hardwired Expansion Zones	32	Keypad Zone Expansion	16	32	Keypad Zone Expansion	16	22	8	onboard zones can be doubled & up to 16 off board zones.	18	16	16
Wireless Expansion Zones	28	28	16	32	28	16	26	16	32	16	16	24
Powered Smoke Zones	1	No	No	No	No	0	1	2	2	1	1	1
<b>Keypad/Access Information</b>												
Max Supervised Keypads	8 hard-wired or wireless	8	8	8	8	4	4	7	7	4	8	8
Max Unsupervised Keypads	Unlimited (hard-wired only)	0	0	0	0	0	0	0	0	0	0	0
Doors of Access	8	0	0	0	0	0	0	0	0	0	0	0
Wiegand Input Keypads	Yes	No	No	No	No	No	No	No	No	No	No	No
Fully Keypad Programmable	Yes	No	Yes	Yes	No	No	No	Yes	Yes	Yes	Yes	Yes
Keypad Compatible w/all Prod	Yes	No	No	No	No	Yes	Yes	No	No	Yes	No	No
<b>Power &amp; Output Information</b>												
Auxiliary Power	600mA	No	550mA	550mA	No	600mA	600mA	650mA	650mA	750mA	1A	600mA
Bell Power	1.5A	No	700mA	700mA	No	2A	2A	2A	2A	1.25A	1.35A	1.85A
Auxiliary Output	4 fully programmable	2	3	14	1	1- 4 relay board	2 open collector outputs	3	3	2	2	4
<b>User Information</b>												
User Codes/Access Cards	30	38	32 + Master	32 + Master Code	38	7	32	16	32	16	8	32
Event Memory	100	128	500	500	128	0	50	256	400	50	No	254
Event Sort	First/Last/Scroll-Keypad	No	Keypad	Keypad	No	0	Keypad	Keypad	Keypad	Keypad	Keypad	Keypad
User Check In (Latchkey children)	Yes	No	No	No	No	No	No	No	No	No	No	No
Individual Zone Monitor	Yes	No	Yes	Yes	No	No	No	No	No	No	No	Yes
<b>MyAccess™ Features</b>												
-Control via Cell Text Messages	Yes	No	No	No	No	Total Connect Service	Total Connect Service	No	No	No	No	No
-Email/Text Messages of System Activity	Yes	No	No	No	No	Total Connect Service	Total Connect Service	No	No	No	No	No
Epad Browser Interface	Yes	No	Yes TL150	Yes TL150	No	Total Connect Service	Total Connect Service	Yes	Yes	No	No	No
Control by an App	Yes	No	No	No	No	Yes	Yes	No	No	Yes	No	No
<b>System Information</b>												
Areas	6	1	0	0	1	1	1	1	1	0	1	2
Partitions	1	1	2	4	1	1	1	1	1	1	1	1
Arming Modes	Area/All-Perim/Home-Sleep-Away	Stay/Away	No	No	Stay/Away	Stay/Away	Stay/Away	Stay/Away	Stay/Away	Stay/Away		
Remote Access Compatible	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Phone Cable Monitor	Yes	Yes	Yes	Yes	Yes	No	Yes	Yes	Yes	No	Yes	Yes

N/A = No Information Available

**DMP XT30 (continued)**

	DMP XT30	DSC Power 432	DSC PC1616	DSC PC1832	DSC Power 632	Ademco Vista-10SE	Ademco Vista 15P	Napco GEM-P816	Napco GEM-P1632	GE Concord Express	Bosch D2212B	Bosch D4412
<b>Communication</b>												
<b>Digital Dialer</b>	SDLC, CID	No	SIA - CID	SIA - CID	No	CID, Sescoa, Standard Pulse Formats	CID, 4X2, Sescoa/Radionics	CID, SIA	CID, SIA	SIA, CID	Modem IIIa2/4-2 (D2212) Modem IIIa2 (D2412)	Modem IIIa2/CID
<b>LAN/WAN Network Communications</b>	Built-in	No	Yes TL 250	Yes TL 250	No	AlarmNet module required	AlarmNet module required	Napco NetLink Module, NL-MOD	Napco NetLink Module, NL-MOD	No	Dialer Capture Module required	Dialer Capture Module required
<b>E-Mail Support</b>	On board Network Communication Allows for E-mail Messages.	No	No	No	No	Requires "Total Connect Service" through Dealer and Honeywell plus additional communications module and service through Honeywell	Requires "Total Connect Service" through Dealer and Honeywell plus additional communications module and service through Honeywell	No	No	No	No	No
<b>Cellular Support</b>	Cellular built-in or add 263G powered by the XT30.	External Add on by third party	External Add on by third party	External Add on by third party	External Add on by third party	External Add on by third party	External Add on by third party	External Add on "Starlink Cellular Module"	External Add on "Starlink Cellular Module"	External Add on by third party	External Add on by third party	External Add on by third party
<b>Wireless Information</b>												
<b>Wireless Arm/Disarm</b>	Yes	Yes	Yes	Yes	Yes	No	Yes	Yes	Yes	Yes	Yes	Yes
<b>Wireless Types Supported</b>	DMP 1100 Series-Ademco - Inovonics - ITI	DSC	DSC 433mHz	DSC 433mHz	DSC	Ademco	Ademco	Gemini	Gemini	ITI	ITI	DS
<b>DMP Exclusive Features</b>												
<b>Attrition Detection</b>	Yes	No	No	No	No	No	No	No	No	No	No	No
<b>Programmable Inactivity Monitor</b>	Yes	No	No	No	No	No	No	No	No	No	No	No
<b>Made in U.S.A.</b>	Yes	No	No	No	No	No	No	No	No	No	No	No
	DMP XT30	DSC Power 432	DSC PC1616	DSC PC1832	DSC Power 632	Ademco Vista-10SE	Ademco Vista 15P	Napco GEM-P816	Napco GEM-P1632	GE Concord Express	Bosch D2212/ D2412	Bosch D4412
<b>False Alarm Reduction Features</b>												
<b>Exit Error</b>	Yes	Yes	No	No	Yes	Yes	Yes	Yes	Yes	Yes	No	Yes
<b>Fire Verify Zones</b>	Yes	Yes	No	No	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
<b>Cross Zoning</b>	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
<b>Abort Reporting</b>	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
<b>System Test by User</b>	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	No	Yes
<b>System Recently Armed</b>	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
<b>Programmable Entry/Exit Delays</b>	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
<b>Transmit Delay</b>	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
<b>Swinger Zone Bypassing</b>	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
<b>Report Bypass to Central Station</b>	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
<b>Unique Duress Code</b>	Yes	Yes	No	No	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
<b>Call Waiting Cancel</b>	Yes	No	No	No	No	No	No	No	No	Yes	No	Yes
<b>Compliance</b>												
<b>ANSI/SIA-CP01 Compliance</b>	Yes	No	Yes	Yes	No	Yes (VISTA-10PSIA)	No	No	No	No	No	No
<b>CSFM</b>	Yes	Yes	Yes	Yes	Yes	Yes	Yes	No	No	Yes	Yes	Yes
<b>ANSI/UL 1023 Household Burglar</b>	Yes	No	No	No	No	Yes	Yes	Yes	Yes	Yes	Yes	Yes
<b>ANSI/UL 1635 Digital Burglar</b>	Yes	No	No	No	No	No	No	No	No	No	Yes	Yes
<b>ANSI/UL 985 Household Fire</b>	Yes	No	Yes	Yes	No	Yes	Yes	No	No	Yes	Yes	Yes

N/A = No Information Available

**DMP XT50**

The DMP XT50 offers everything you want in one panel - built-in 1100 Wireless Receiver plus Network, Cellular, and Dialer communications. The XT30 can be expanded to 30 zones by adding hardwire zones or 1100 Series wireless zones to meet the protection requirements of any mid-range and high-end residential or commercial installation. The XT30 provides 10 on-board zones, one 2-wire smoke detector zone, 20 keypad bus zones, door access capability, ethernet, cellular, Pager Direct™ paging, 30 user codes, and daily opening/closing and relay output schedules.

**Compares to:**

Ademco Vista 205E, Vista 30PSE  
 DSC PC1832, PC1864, Power 832  
 Bosch D6412, D7212GV3

	DMP XT50	Bosch D6412	Bosch D7212GV3	DSC PC1832	DSC PC1864	DSC Power 832	Ademco Vista-20SE	Ademco Vista-30PSE
<b>Zone Information</b>								
Maximum Zones	58	40	40	32	64	32	38	32
Control Panel Zones	10	8	8	8	8	8	8	2
Control Panel Fire Zones	1	1	0	No	No	1	1	4 wire
Hardwired Expansion Zones	32	32	32	32	32	32	8	8
Wireless Expansion Zones	48	40	32	32	32	32	30	30
Powered Smoke Zones	1	1		No	No	1	1	4 wire
<b>Keypad/Access Information</b>								
Max Supervised Keypads	8 hard-wired or wireless (See LT-0980)	8	8	8	8	12	8	4
Max Unsupervised Keypads	unlimited (hard-wired only)	0	32	0	0	0	0	0
Doors with Door Control	8	0	0	0	0	0	0	0
Wiegand Input Keypads	Yes	No	No	No	No	No	No	No
Fully Keypad Programmable	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Keypad Compatible w/ all Prod	Yes	No	No	No	No	No	No	No
<b>Power &amp; Output Information</b>								
Auxiliary Power	600mA	600mA	1.4A	550mA	550mA	550mA	400mA	500mA
Bell Power	1.5A	1.85A	2.0A	700mA	700mA	700mA	2A	2A
Auxiliary Output	4 fully programmable	1 Onboard 2 Open collectors	3	14	17	2	2 trigger outputs	4 on off board relay module
<b>User Information</b>								
User Codes/Access Cards	99	32	99	32 + Master Code	32 + Master Code	38	15 per partition	7
Event Memory	200	254	1000	500	500	128	48	No
Event Sort	First/Last/Scroll-Keypad	Keypad	Keypad	Keypad	Keypad	Keypad	Keypad	No
User Check In (Latchkey children)	Yes	No	No	No	No	No	No	No
Individual Zone Monitor	Yes	Yes	No	Yes	Yes	Yes	No exit points only	No
<b>MyAccess™ Features</b>								
-Control via Cell Text Messages	Yes	No	No	No	No	No	Total Connect Service	Total Connect Service
-Email/Text Messages of System Activity	Yes	No	No	No	No	No	Total Connect Service	Total Connect Service
Epad Browser Interface	Yes	No	No	Yes TL150	Yes TL150	No	Total Connect Service	Total Connect Service
<b>System Information</b>								
Areas	6	4	4	0	0	1	2	1
Partitions	1	1	1	4	8	2	2	1
Arming Modes	Area/All-Perim/Home-Sleep-Away	Area/ All-Perim/Common Shared Areas	4 programmable areas w/ Perim/Interior partitioning (regular, master, associate, or shared options)	No	No	Stay/Away	Area/Common Area/Stay-Away	Stay/Away
Remote Access Compatible	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Phone Cable Monitor	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes

**DMP XT50 (continued)**

	<b>DMP XT50</b>	<b>Bosch D6412</b>	<b>Bosch D7212GV3</b>	<b>DSC PC1832</b>	<b>DSC PC1864</b>	<b>DSC Power 832</b>	<b>Ademco Vista-20SE</b>	<b>Ademco Vista-30PSE</b>
<b>Communication</b>								
<b>Digital Dialer</b>	SDLC, CID	CID, Modem IIIa2	Modem IIIa2, BFSK	SIA - CID	SIA - CID	SIA, CID	CID, 4X2,Sescoa/Radionics, 3X1	CID, 4X2,Sescoa/Radionics, 3X1
<b>LAN/WAN Network</b>	Yes, Onboard	C900TTL-E	DX4020	Yes TL 250	Yes TL 250	No	AlarmNet Module required	No
<b>E-Mail Support</b>	On board Network Communication Allows for E-mail Messages. Up to 3 e-mail addresses.	No	No	No	No	No	Requires "Total Connect Service" through Dealer and Honeywell plus additional communications module and service through Honeywell	Requires "Total Connect Service" through Dealer and Honeywell plus additional communications module and service through Honeywell
<b>Cellular Support</b>	Can be ordered with GPRS cellular built-in or add the 263G cellular unit directly on the XT50 and powered by the XT50.	External Add on by third party	Yes; ITS-DX4020-G, GSM?GPRS Module	External Add on by third party	External Add on by third party	External Add on by third party	External Add on by third party	External Add on by third party
<b>Wireless Information</b>								
<b>Wireless Arm/Disarm</b>	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
<b>Built-in Wireless Receiver</b>	Yes	No	No	No	No	No	No	No
<b>Wireless Types Supported</b>	DMP 1100 Series - Ademco - Inovonics - ITI	DS	Inovonics	DSC 433mHz	DSC 433mHz	DSC	Ademco	Ademco
<b>False Alarm Reduction Features</b>								
<b>Exit Error</b>	Yes	Yes	No	No	No	Yes	Yes	Yes
<b>Fire Verify Zones</b>	Yes	Yes	Yes	No	No	Yes	Yes	No
<b>Cross Zoning</b>	Yes	Yes	Yes	Yes	Yes	Yes	Yes	No
<b>Abort Reporting</b>	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
<b>System Test by User</b>	Yes	Yes	Yes	Yes	Yes	Yes	Yes	No
<b>System Recently Armed</b>	Yes	Yes	No	Yes	Yes	Yes	Yes	Yes
<b>Programmable Entry/Exit Delays</b>	Yes	Yes	Yes	Yes	Yes	Yes	Yes	No
<b>Transmit Delay</b>	Yes	Yes	Yes	Yes	Yes	Yes	Yes	No
<b>Swinger Zone Bypassing</b>	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
<b>Report Bypass to Central Station</b>	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
<b>Unique Duress Code</b>	Yes	Yes	Yes	No	No	No	No	No
<b>Call Waiting Cancel</b>	Yes	Yes	No	No	No	No	No	No
<b>DMP Exclusive Features</b>								
Attrition Detection	Yes	No	No	No	No	No	No	No
Programmable Inactivity Monitor	Yes	No	No	No	No	No	No	No
<b>Made in U.S.A.</b>	Yes	No	No	No	No	No	No	No
<b>Compliance</b>								
<b>ANSI/SIA-CP01 Compliance</b>	Yes	No	No	Yes	Yes	No	No	No
<b>CSFM</b>	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
<b>ANSI/UL 1023 Household Burglar</b>	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
<b>ANSI/UL 1635 Digital Burglar</b>	Yes	Yes	Yes	No	No	No	No	No
<b>ANSI/UL 985 Household Fire</b>	Yes	Yes	Yes	No	No	Yes	Yes	Yes

**DMP XR100 and XR100N**

The DMP XR100 and XR100N Command Processor™ Panels provide a combination of capability, sophistication, and simple operation to make this panel the obvious choice for your burglary, fire, and access control applications. The XR100 Series provides 10 on-board zones, up to 142 programmable zones, 142 programmable outputs, 102 programmable Form C outputs, and 10,000 User Codes with 99 separate profiles. The XR100N offers on-board network support. Program common areas, cross-zoned areas, primary and secondary schedules, temporary and permanent schedules, output schedules, and view a history of up to 12,000 events. Compatible with the DMP 1100 Series Two-Way Wireless, providing support for up to 100 DMP Wireless devices.

**Compares to:**

- Ademco Vista 128FBP
- DSC MAXSYS PC4020
- GE Interlogix Concord Ultra, Advent 60-562-03
- Bosch D7412GV3
- FBII XL-5
- ITI Concord 60-734-01, 60-746-01

	DMP XR100/XR100N	Bosch D7412GV3	Ademco Vista-128FBP	FBII XL-5	GE Interlogix Concord Ultra	GE Interlogix Advent (60-562-03)	DSC MAXSYS PC4020	ITI Concord 60-734-01 60-746-01
<b>Zone Information</b>								
Maximum Zones	142	75	128	128	96	132	128	76
Control Panel Zones	10	8	8	8	8	8	16	8
Control Panel Fire Zones	2	No	2	No	1	1	No	1
Hardwired Expansion Zones	132		120	120	96	No	112	68
Wireless Expansion Zones	DMP1100 Series (100 Zones)	67	128	No	96	132	64	76
Powered Smoke Zones	2 onboard expandable to 102		2	No	1	1	4 wire from SAUX	Yes
Maximum 2-Wire Smoke Detectors	12 (521B) per zone, Maximum 130 zones		No	No	No	No	No	No
<b>Keypad/Access Information</b>								
Max Supervised Keypads	8 hardwired or wireless	16	16 Keypads or 6 touch screen keypads	16	SuperBus 2000 Devices up to 16	SuperBus 2000 Devices up to 31 - no more than 62 per panel including keypads, zone expanders, output modules	16	16 Devices on Superbus
Max Unsupervised Keypads	Unlimited (hard-wired only)	32	No	No	No	No	No	0
Doors of Access	8	2	8 doors (V-Ples Access Control) expandable to 16 w/ Vista Gateway Module connected to Northern Computer Passpoint Access System	No	No	No	Up to 16 dual reader modules for a total of 32 readers	0
Wiegand Input Keypads	Yes	0	No	No	No	No	No	No
Fully Keypad Programmable	Yes	Yes (v8.11 or higher)	No	Yes	Yes	Yes	Yes	Yes
Keypad Compatible with all Products	Yes	No	No	No	No	No	No	2 Different Keypad Styles
<b>Power &amp; Output information</b>								
Auxiliary Power	1.5A	1.4A	1A	900mA	1.35A	5A	500mA shared with SAUX	2A
Bell Power	1.5A	2.0A	2.3A divided between two bell circuits	2A	12 Watt Siren driver	Voice Siren Driver output 4.8 Ohms at 25 Watts	700mA	12 watt voice siren driver built in
Auxiliary Output	2 Form C 4 open collector onboard 100 expandable	3	1 onboard expandable to 96 relays	8 voltage trigger outputs 40 programmable relay outputs	2	4	64	2 open collectors, 200mA (Maximum)
<b>User Information</b>								
User Codes/Access Cards	10,000	99/396 tokens	150 User Codes/250 Cards using VistaKey	128 with 7 authority levels	230	100	1,000	60
Event Memory	12,000 Events: 10,000 Access events and 2,000 system events	1000	512	128	250	2,048	3,000	100
<b>MyAccess™ Features</b>								
-Control via Cell Text Messages	Yes	No	Total Connect Service	No	No	No	No	No
-Email/Text Messages of System Actvty	Yes	No	Total Connect Service	No	No	No	No	No
Event Sort	View opening/closing, zone, user code, schedule changes, door access, and sup events. Sort by user, door, and date range via keypad or remote PC Access.	Keypad	Keypad	Keypad	Keypad	Keypad	2,800 Viewable on Keypad	Keypad
Phone Control	No	No	Yes (requires external module)	No	No	Yes	No	No
2 Way Voice	Eagle Products	Eagle Products	No	No	No	No	No	Yes w/Interrogator 200
Zone Monitor	Yes	Yes	Perimeter only	Yes	No	Yes Perimeter only	No	No
Epad Browser Interface	Yes	No	Yes requires AlarmNet-I (must use 3rd party Ademco AlarmNet-I Server)	No	No	No	Using T-Link: 255 accounts over Proprietary Lan/Wan Intranet	NO

N/A = No Information Available

**DMP XR100 and XR100N (continued)**

	DMP XR100/XR100N	Bosch D7412GV3	Ademco Vista-128FBP	FBI XL-5	GE Interlogix Concord Ultra	GE Interlogix Advent (60-525-03)	DSC MAXSYS PC4020	ITI Concord 60-734-01 60-746-01
<b>System Information</b>								
E-Mail	Yes via GSM/GPRS	No	Total Connect Service	No	No	No	No	No
SMS TXT Messaging	Yes	No	Total Connect Service	No	No	No	No	No
Reporting	Serial III, CID, SDLC	Modem IIIa2, CID	Ademco Low Speed, 4+2 Express, High Speed, Contact ID, Sescoa and Radionics	10PPS, 20PPS, 40PPS 4X2, FBI Super Fast, BFSK, Ademco Express and Point ID	SIA, CID	CID	10 bps, 20 bps at 1400/2300 Hz handshake, CID and SIA	SIA, CID
Areas	8	8	8	7 Areas + 1 Common Area	2	4	8	2
Arming Modes	Area/All-Perim/ Home-Sleep-Away	Area/Associate/Master/Shared	Area/ Common Area and Stay/Away	Area	Area	Area	Area	Stay/Away
Remote Access Compatible	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Phone Cable Monitor	Yes	No	No	Yes	Yes	No	No	No
Parts Compatible Across all Product Lines	Yes	No	No	No	No	No	No	No
LAN/WAN Network Communications	Built-in Network Alarm Router (XR100N)	DX4020 Network Interface Module	Yes requires AlarmNet-I (must use 3rd party Ademco AlarmNet-I Server)	No	No	No	No	No
<b>Wireless Information</b>								
Wireless Arm/Disarm	Yes	Yes	Yes	No	Yes	Yes	Yes	Yes
Wireless Types Supported	DMP1100 Series (100 Zones)	Inovonics	Ademco	No	ITI	ITI	DSC	ITI
<b>False Alarm Reduction Features</b>								
Cancel/Verify	Yes	No	No	No	No	No	No	No
Exit Error	Yes	No	Yes	Yes	Yes	No	Yes	Yes
Fire Verify Zones	Yes	Yes	Yes	Yes	Yes	No	No	Yes
Cross Zoning	Yes	No	Yes	Yes	Yes	No	Yes	Yes
Abort Reporting	Yes	Yes	No	Yes	Yes	Yes	Yes	Yes
System Test by User	Yes	Yes	Yes	No	No	No	No	Yes
System Recently Armed	Yes	No	Yes	No	Yes	No	Yes	Yes
Programmable Entry/Exit Delays	Yes	Yes	Yes	2 entry delays	Yes	Yes	No	Yes
Transmit Delay	Yes	Yes	No	No	Yes	Yes	Yes	Yes
Swinger Zone Bypassing	Yes	Yes	No	No	Yes	Yes	Yes	Yes
Report Bypass to Central Station	Yes	Yes	No	No	Yes	Yes	No	Yes
Unique Duress Code	Yes	Yes	No	Ambush code capability	Yes	No	No	Yes
Call Waiting Cancel	Yes	No	Yes	No	Yes	No	No	Yes
Meets ANSI/SIA CP-01	Yes	No	Yes requires Vista-128 PSIA	No	Yes	No	No	No
Multi-lingual Menus Available	English/Spanish/French	No	No	No	No	No	No	No
<b>Compliance</b>								
California State Fire Marshal (CSFM)	Yes	Yes	Yes	No	Yes	Yes	Yes	Yes
MEA New York City	Yes	Yes	Yes	No	No	No	No	No
NIST Certification	Yes	No	No	No	No	No	No	No
UL 365 Police Connected Burg	Yes	Yes	Yes	No	No	Yes	Yes	Yes
UL 609 Local Burglar	Yes	Yes	Yes	No	No	Yes	Yes	Yes
UL 1023 Household Burglar	Yes	Yes	Yes	No	Yes	Yes	Yes	Yes
UL 1076 Proprietary Burglar	Yes	No	No	No	No	No	No	No
UL 1610 Central Station Burg	Yes	Yes	Yes	No	No	Yes	Yes	Yes
UL 1635 Digital Burglar	Yes	Yes	No	No	Yes	Yes	Yes	No
UL 985 NFPA 74 Household Fire Warning	Yes	Yes	Yes	No	Yes	Yes	Yes	No
UL 294 Access Control System Units	Yes	No	No	No	No	No	No	No
UL 864 Fire Protective Signaling Systems	Yes	Yes	Yes	No	No	No	Yes	No
Made in U.S.A.	Yes	No	No	No	No	No	No	No

N/A = No Information Available

**DMP XR500/XR500N/XR500E**

The DMP XR500, XR500N, and XR500E Command Processor™ Panels provide dealers and end-users with an integrated feature package. With an extensive feature set this panel the obvious choice for all your burglary, fire, and access control applications. The XR500 Series provides 10 on-board zones, up to 574 programmable zones, 574 programmable outputs, 502 programmable Form C relays, and 10,000 User Codes with 99 separate profiles. The XR500N and XR500E offer on-board network support. The XR500E also offers built-in Encryption and secure passphrase option. Program common areas, cross-zoned areas, primary and secondary schedules, temporary and permanent schedules, output schedules, and view a history of up to 12,000 events. Compatible with the complete line of DMP 1100X Series Two-Way Wireless, providing support for up to 500 DMP Wireless devices.

**Compares to:**

AdemcoVista-128BP, Vista-250BP  
 DSC MAXSYS PC4020  
 Bosch D9412GV3  
 GE AL-4017 Alliance  
 GE Interlogix Concord Ultra, Advent 60-562-01, NX-8E  
 Pacom 1057, 1058  
 FBII XL-5

	DMP XR500	DMP XR500N/ XR500E	Bosch D941GV3	GE AL-4017 Alliance	Ademco Vista-128BP	Ademco Vista-250BP	FBII XL-5	GE Interlogix Concord Ultra	GE Interlogix Advent 60-562-01	GE Interlogix NX-8E	DSC MAXSYS PC4020	Pacom 1057	Pacom 1058
<b>Zone Information</b>													
<b>Maximum Zones</b>	574	574	246	256	128	250	128	96	250	192	128	256	256
<b>Control Panel Zones</b>	10	10	8	16	8	8	8	8	8	8	16	No	8
<b>Control Panel Fire Zones</b>	2	2	0	No	2	2	No	1	1	No	No	None	None
<b>Hardwired Expansion Zones</b>	564	564	238	240	120	242	120	96	242	184	112	No	255
<b>Wireless Expansion Zones</b>	DMP 1100 Series (500 Zones)	DMP 1100 Series (500 Zones)	238	No	128 UL Listed for Commercial Burg and Fire	250 UL Listed for Commercial Burg and Fire	No	96	250	192	64	Requires 1066-INOV Module	No
<b>Powered Smoke Zones</b>	2 onboard 560 off-board	2 onboard 560 off-board	Requires D125B Powered Loop interface module	No	2	2	No	1	1	No	4-wire from SAUX	None	None
<b>Maximum 2-Wire Smoke Detectors</b>	12 (521B) per zone, Maximum 562 zones	12 (521B) per zone, Maximum 562 zones	No	No	No	No	No	No	No	No	No	No	No
<b>Keypad/Access Information</b>													
<b>Max Supervised Keypads</b>	16 hard-wired or wireless (See LT-0681)	16	16	16	16 Keypads or 6 touch screen keypads	16 Keypads or 6 touch screen keypads	16	SuperBus 2000 Devices up to 16	Up to 31 SuperBus 2000 Devices per Bus no more than 62 per panel. These include keypads, Zone Expanders, Output modules, etc.	32 unknown if all are supervised	16	8	16
<b>Max Unsupervised Keypads</b>	Unlimited (hard-wired only)	Unlimited	32	0	No	No	No	No	No	No	No	No	No
<b>Doors of Access</b>	16	16	8	16 standard expandable to 64	8 doors expandable to 16 using Vista Gateway Module	15	No	No	No	No	Up to 16 dual reader modules for a total of 32 readers	64	16
<b>Wiegand Input Keypads</b>	Yes	Yes	0	Yes	No	No	No	No	No	No	No	Yes	Yes
<b>Fully Keypad Programmable</b>	Yes	Yes	Yes / limited	No	No	No	Yes	Yes	Yes	No	Yes	Yes	Yes
<b>Keypad Compatible with all Products</b>	Yes	Yes	No	No	No	No	No	No	No	No	No	No	No
<b>Power &amp; Output information</b>													
<b>Auxiliary Power</b>	1.5A	1.5A	1.4A	300mA	1A	1A	900mA	1.35A	5A	2A-unknown if shared w/Bell output	500mA shared with SAUX	2A	No
<b>Bell Power</b>	1.5A	1.5A	2A	No	2.3A divided between two bell circuits	2.3A divided between two bell circuits	2A	12 Watt Siren driver	Siren Driver output 4.8 Ohms at 25 Watts	No	700mA	2A	No
<b>Auxiliary Output</b>	2 Form "C" 4 Open Collector outputs onboard expandable to 500 outputs offboard	2 Form "C" 4 Open Collector outputs onboard expandable to 500 outputs offboard	8 onboard Form C and expandable off board to 238 for 246 relays overall	16 onboard expandable to 256	1 onboard expandable to 96 relays	1 onboard expandable to 96 relays	8 voltage trigger outputs 40 programmable relay outputs	2	4	No	64	64 Form C 64 Open Collector	64 Form C 64 Open Collector

**DMP XR500/XR500N/XR500E (continued)**

	DMP XR500	DMP XR500N/ XR500E	Bosch D9412GV3	GE AL-4017 Alliance	Ademco Vista-128BP	Ademco Vista-250BP	FBI XL-5	GE Interlogix Concord Ultra	GE Interlogix Advent (60-562-01)	GE Interlogix NX-8E	DSC MAXSYS PC4020	Pacom 1057	Pacom 1058
<b>User Information</b>													
<b>User Codes/Access Cards</b>	10,000	10,000	249 User Codes/ 996 Tokens	50 Standard Cardholders expandable to 65,535 or up to 1000 pin codes	150 User Codes and 250 Cards using VistaKey	250 User Codes and using V-Plex Vista Key Access Control up to 500 cards	128 with 7 authority levels	230	250	240	1500 w/ 64 access levels	10,000	1,000
<b>Event Memory</b>	12,000	12,000	1000	1000 alarm events 1,000 door access events.	512	1000	128	250	2,048	512	3000	5,000	1,000
<b>MyAccess™ Features</b>													
<b>-Control via Cell Text Messages</b>	Yes	No	No	No	Total Connect Service	Total Connect Service	No	No	No	No	No	No	No
<b>-Email/Text Messages of System Activity</b>	Yes	No	No	No	Total Connect Service	Total Connect Service	No	No	No	No	No	No	No
<b>Event Sort</b>	View opening/closings, zone events, user code and schedule changes, door access, and supervisory events. Sort by user, door, and date range via keypad or remote PC Access.	View opening/closings, zone events, user code and schedule changes, door access, and supervisory events. Sort by user, door, and date range via keypad or remote PC Access.	Keypad	No	Keypad	Keypad	Keypad	Keypad	Keypad	No	2800 Viewable on Keypad	Sort by Date or All	Sort by Date or All
<b>2 Way Voice</b>	Eagle Products	Eagle Products	Eagle Products	No	Yes	Yes	No	No	No	No	No	No	No
<b>Zone Monitor</b>	Yes	Yes	Yes	No	Perimeter only	Perimeter only	Yes	No	Yes Perimeter only	No	No	No	No
<b>Epad Browser Interface</b>	Yes	Yes	No	No	Yes requires third party Ademco AlarmNet-I Server	Yes requires third party Ademco AlarmNet-I Server	No	No	No	No	No	No	No
<b>System Information</b>													
<b>E-Mail</b>	Yes via GSM/GPRS	No	No	No	Total Connect Service	Total Connect Service	No	No	No	No	No	No	No
<b>SMS TXT Messaging</b>	Yes	No	No	No	Total Connect Service	Total Connect Service	No	No	No	No	No	No	No
<b>Reporting</b>	CID, Serial 3	CID, Serial 3	Modem IIIa2, CID	CID, SIA, XSIA,	Ademco Low Speed, 4+2 Express, High Speed, CID, Sescoa/Radionics	Ademco Low Speed, 4+2 Express, High Speed, CID, Sescoa/Radionics	10PPS, 20PPS, 40PPS 4X2, FBI Super Fast, BFSK, Ademco Express and Point ID	SIA, CID	CID	SIA, CID	10 bps, 20 bps at 1400/2300 Hz handshake, CID, SIA	No	No
<b>Areas</b>	32	32	32	16	8	8	7 Areas + 1 Common Area	2	8	8	8	8	32
<b>Partitions</b>	32	32	32	1	8	8	7 Areas + 1 Common Area	2	8	8	8	8	32
<b>Arming Modes</b>	Area/ Common Areas/ All-Perimeter/ Home-Sleep-Away	Area/ Common Areas/ All-Perimeter/ Home-Sleep-Away	Area/ Associate/ Master/ Shared	Area/Common Area	Area/ Common Area and Stay/Away	Area/ Common Area and Stay/Away	Area	Area	Area	PartitioNorea	Area	PartitioNorea	Area, All/Perim
<b>Remote Access Compatible</b>	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	No	Yes	No	No
<b>Phone Cable Monitor</b>	Yes	Yes	Yes	No	No	No	Yes	Yes	Yes	No	No	No	No
<b>Flash Updateable</b>	Yes	Yes	No	No	No	No	No	No	No	No	No	No	No
<b>Parts Compatible Across all Product Lines</b>	Yes	Yes	No	No	No	No	No	No	No	No	No	No	No
<b>LAN/WAN Network Communications</b>	Requires 462N/iCOM or iCOM-E	XR500N has Built-in Network Alarm Router - XR500E has AES Encryption	DX4020 Required	Yes	Yes requires third party Ademco AlarmNet-I Server	Yes requires third party Ademco AlarmNet-I Server	No	No	No	No	Yes	No	No
<b>Wireless Information</b>													
<b>Wireless Arm/Disarm</b>	Yes	Yes	Yes	No	Yes	Yes	No	Yes	Yes	Yes	Yes	No	No
<b>Wireless Types Supported</b>	DMP 1100 Series Wireless – up to 500 zones/ Inovonics/ ITI/Ademco	DMP 1100 Series Wireless – up to 500 zones/ Inovonics/ITI/Ademco	Inovonics	No	Ademco	Ademco	No	ITI	ITI	ITI	DSC	Inovonics	Inovonics

N/A = No Information Available

**DMP XR500/XR500N/XR500E (continued)**

	DMP XR500	DMP XR500N/ XR500E	Bosch D9412GV3	GE AL-4017 Alliance	Ademco Vista-128BP	Ademco Vista-250BP	FBI XL-5	GE Interlogix Concord Ultra	GE Interlogix Advent (60-562-01)	GE Interlogix NX-8E	DSC MAXSYS PC4020	Pacom 1057	Pacom 1058
<b>Banking Features</b>													
Two Man Rule	No	Yes	Yes	No	No	No	No	No	No	No	No	No	No
Early Morning Ambush	No	Yes	Yes	No	No	No	No	No	No	No	No	No	No
Panic/Hold-up Button Test	No	Yes	Yes	No	No	No	No	No	No	No	No	No	No
Bank Safe & Vault	No	Yes	Yes	No	No	No	No	No	No	No	No	No	No
On-Board Ethernet	No	Yes	No	No	No	No	No	No	No	No	No	No	No
Arm First Area	Yes	Yes	Yes	No	No	No	No	No	No	No	No	No	No
<b>False Alarm Reduction Features</b>													
Cancel/Verify	Yes	No	No	No	No	No	No	No	No	No	No	No	No
Exit Error	Yes	Yes	No	No	Yes	Yes	Yes	Yes	Yes	No	Yes	No	No
Fire Verify Zones	Yes	Yes	Yes	No	Yes	Yes	Yes	Yes	Yes	No	No	No	No
Cross Zoning	Yes	Yes	No	No	Yes	Yes	Yes	Yes	Yes	Yes	Yes	No	No
Abort Reporting	Yes	Yes	Yes	No	No	No	Yes	Yes	Yes	No	Yes	No	No
System Test by User	Yes	Yes	Yes	No	Yes	Yes	No	No	Yes	No	No	No	No
System Recently Armed	Yes	Yes	No	No	Yes	Yes	No	Yes	Yes	No	Yes	No	No
Programmable Entry/Exit Delays	Yes	Yes	Yes	No	Yes	Yes	2 entry delays	Yes	Yes	No	No	No	No
Transmit Delay	Yes	Yes	Yes	No	No	No	No	Yes	Yes	No	Yes	No	No
Swinger Zone Bypassing	Yes	Yes	Yes	No	No	No	No	Yes	Yes	No	Yes	No	No
Report Bypass to Central Station	Yes	Yes	Yes	No	No	No	No	Yes	Yes	No	No	No	No
Unique Duress Code	Yes	Yes	Yes	No	No	No	Ambush code capability	Yes	Yes	No	No	No	No
Call Waiting Cancel	Yes	Yes	No	No	Yes	Yes	No	Yes	Yes	No	No	No	No
Meets ANSI/SIA CP-01	Yes	Yes	No	No	Yes requires Vista-128 PSIA	Yes requires Vista-250 PSIA	No	Yes	No	No	No	No	No
Multi-lingual Menus Available	Yes	Yes	No	No	No	No	No	No	No	No	No	No	No
<b>Compliance</b>													
UL 365 Police Connected Burg	Yes	Yes	Yes	Yes	Yes	Yes	No	No	Yes	No	Yes	No	No
UL 609 Local Burglar	Yes	Yes	Yes	Yes	Yes	Yes	No	No	Yes	No	Yes	No	No
UL 1023 Household Burglar	Yes	Yes	Yes	No	No	No	No	Yes	Yes	No	Yes	No	No
UL 1076 Proprietary Burglar	Yes	Yes	No	No	No	No	No	No	No	No	No	No	No
UL 1610 Central Station Burg	Yes	Yes	Yes	Yes	Yes	Yes	No	No	Yes	No	Yes	No	No
UL 1635 Digital Burglar	Yes	Yes	Yes	Yes	No	No	No	Yes	Yes	No	Yes	No	No
UL 985 NFPA 74 Household Fire Warning	Yes	Yes	Yes	No	Yes	Yes	No	Yes	Yes	No	Yes	No	No
UL 294 Access Control System Units	Yes	Yes	Yes	Yes	No	No	No	No	No	No	No	Yes	Yes
UL 864 Fire Protective Signaling Systems	Yes	Yes	Yes	No	Yes	Yes	No	No	No	No	Yes	No	No
NIST Certification	Yes	Yes	No	No	No	No	No	No	No	No	No	No	No
Underwriters Laboratories Canada (ULC)	Yes	Yes	Yes	No	No	No	No	No	No	No	Yes	Yes	Yes
California State Fire Marshal (CSFM)	Yes	Yes	Yes	No	Yes	Yes	No	Yes	Yes	No	Yes	No	No
MEA New York City	No	No	Yes	No	Yes	Pending	No	No	No	No	No	No	No
<b>Made in U.S.A.</b>	Yes	Yes	No	No	No	No	No	No	No	No	No	No	No



800-641-4282  
www.dmp.com  
Made in the USA

INTRUSION • FIRE • ACCESS • NETWORKS  
2500 North Partnership Boulevard  
Springfield, Missouri 65803-8877

MADE IN  U.S.A.  
LI-2035 © 2012 Digital Monitoring Products, Inc. 01/12

