



Search dmpalarms



FDNY



Fire annunciation solutions —



DMP Fire Command Keypads provide a variety of fire annunciation solutions for residential and commercial fire applications.

The 630F provides 32-character full text LCD display of system events and menu prompts for efficient, easy use.

The keypad offers simple, one-button access to common features, including:

- Silence alarms
- Reset sensors
- Test the system
- Perform a fire drill

630F DMP FIRE COMMAND KEYPAD

FEATURES

- Simple harness connection to 4-wire keypad bus
- At-a-glance system status
- Powered from panel or auxiliary power supply
- Optional backboxes for conduit or wall mount applications
- Attractive non-obtrusive designs
- 2-button Panic keys
- 32-character LCD display
- Flush or Surface mount
- Keyswitch enables single button operation
- Full operation with authorized code
- Built-in diagnostics
- AC Power, Trouble, Alarm LED
- Compatible with XR100/XR500 Series
- System events display in plain English



Digital Monitoring Products

630F Fire Command Keypad

630F REMOTE ANNUNCIATOR

The 630F Fire Command Center offers a 32-character full text LCD readout that displays system events and menu prompts, making it efficient and easy-to-use. The backbox and trim frame provide an attractive installation. The keypad can either be flush-mounted or surface-mounted.



630F Keypad

SINGLE-BUTTON OPERATION

The 630F Fire Command Center has a factory installed keyswitch that enables the four function buttons—Alarm Silence, System Reset, System Test, and Fire Drill. The user can also access these four functions and many more through the User Menu by entering a valid user code.

BUILT-IN DIAGNOSTICS

An internal diagnostics program lets installers and service technicians test the operation of the keypad at any time without disabling the system.

SUPERVISED AND UNSUPERVISED OPERATION

The 630F keypad can be programmed for supervised or unsupervised operation on the keypad data bus, increasing the overall number of keypads you can install to provide maximum flexibility. When supervised, the keypad occupies its own address. Unsupervised operation allows you to install multiple keypads on the bus with the same address.

STATUS LEDs

The Green Power LED turns on when primary AC or DC power to the panel is at an acceptable level and flashes when its battery is low or missing.

A Yellow Trouble LED turns on when either the panel has failed to communicate with the central station receiver or when phone line 1 or 2 is in a bad condition.

630F SPECIFICATIONS

Operating Voltage	8.5 to 15 VDC
Current Draw	63mA standby 92mA maximum
Trim Frame Dimensions	10.4" W x 7.0" H x 1.7" D
Backbox Dimensions	8.75" W x 6.375" H x 2.5" D
Panel Compatibility	XR100 and XR500 Series Panels

KEYPAD ACCESSORIES

635	1.75" 630F Alternate Surface Mount Backbox
635F	2.5" 630F Flush Mount Replacement Backbox
300	4-wire Replacement Harness

LISTINGS AND APPROVALS

California State Fire Marshal (CSFM)
New York City (FDNY COA #6055)
FCC Part 15
Underwriters Laboratories (UL) Listed
ANSI/UL 864 Control Units for Fire Protective Signaling
ANSI/UL 985 Household Fire Warning
For additional information, access www.dmp.com and select Compliance.

