

## SCS-101 IMPORTANT COMPATIBILITY INFORMATION

### Compatible Levels and Versions

The SCS-101 Level E and Version 200 or higher can ONLY be used with SCS-1R Receivers with firmware Version 903 or higher and is NOT compatible with the SCS-1 Receiver.

The SCS-101 line card Level D and Version 103 or lower can ONLY be used with the SCS-1R Version 902 or lower or SCS-1 Receivers.

As needed refer to SCS-101 Network Interface Card Installation Guide (LT-0320) or the SCS-1R Installation and Programming Guide (LT-0717).

### Troubleshooting Notes

If an SCS-101 Version 103 is installed in an SCS-1R Version 903 Receiver, no network panel messages can be received by the SCS-1R. The panel keypad displays Network Trouble and the receiver sends an S81 Warning: Network Card Trouble message.

If an SCS-101 Version 200 is installed in an SCS-1R Version 902 Receiver, network panel checkin messages are received and acknowledged by the SCS-101, but these checkin messages are not processed by the SCS-101 and panel supervision does not occur. All other panel messages (Alarm, Trouble, etc.) are not received or acknowledged and are ignored. The panel keypad displays Network Trouble but there is no indication at the SCS-1R Receiver.